

MNDC-C : Mini DC Wiring Panel by Midnite Solar



Price: CAD \$319.00

SKU: MNDC-C

Product Categories: [Wiring Panels](#), [Cables & Wiring Kits](#), [Disconnects](#), [E-Panels](#), [Inverters](#), [Shop](#), [Wiring & BOS](#)

Product Tags: [breaker box](#), [breaker panel](#), [canada](#), [dc breaker box](#), [dc disconnect](#), [distribution panel](#), [midnite](#), [midnite solar](#), [mini](#), [mndc](#), [mndc-c](#), [mndc-c canada](#), [mndc-c-series](#), [panel](#), [power panel](#)

Product Page: <https://www.modernoutpost.com/product/mndc-c-mini-dc-disconnect-by-midnite-solar/>

Product Summary

The MNDC-C-Series is an MNDC wiring panel & breaker box with adapter attached for the smaller panel mount inverter breakers (3/4 inch MNEDC panel mount breaker not included). Chassis is white powder coated aluminum with 5 din rail breaker slots or 3 panel mount breaker slots. This is the same box as the [MNDC175](#) & [MNDC250](#).

Main inverter breaker, and DIN rail breakers NOT included in this model - available separately. 125A, [175A](#), [250A](#).

Product Description

The MNDC-C-Series is an MNDC wiring panel & breaker box with adapter attached for the smaller panel mount inverter breakers (3/4 inch MNEDC panel mount breaker not included). Chassis is white powder coated aluminum with 5 din rail breaker slots or 3 panel mount breaker slots. This is the same box as the [MNDC175](#) & [MNDC250](#).

Main inverter breaker, and DIN rail breakers NOT included in this model - available separately. 125A, [175A](#), [250A](#).

The MNDC comes with a din rail for 5 additional DC breakers for DC loads, charge controller disconnect, battery status monitor feed etc. included is a ground bus, 5/16" bonding battery minus stud. Mounting holes for a 500 amp shunt are built in. ETL listed for US and Canada.

MNDC-C Specifications

Dimensions : 17"L x 9"W x 4"D

Weight : 6lbs / 2.73kg

Product Attributes

- Dimensions: 1 × 1 × 1 cm
- Weight: 2.9 kg