

MNDC175 : DC Wiring Panel with 175A Breaker by Midnite Solar



Price: CAD \$429.00

SKU: MNDC175

Product Categories: [Wiring Panels](#), [Disconnects](#), [Shop](#), [Wiring & BOS](#)

Product Tags: [175a](#), [175a inverter breaker](#), [breaker panel](#), [canada](#), [inverter disconnect](#), [inverter disconnect breaker](#), [inverter wiring](#), [midnite](#), [midnite mndc175](#), [midnite mndc175 canada](#), [midnite solar](#), [mndc175](#), [mndc175 canada](#), [wiring box](#)

Product Page:

<https://www.modernoutpost.com/product/mndc175-dc-wiring-panel-with-175a-breaker-by-midnite-solar/>

Product Summary

The MNDC175 175A DC Wiring Panel & Inverter Disconnect by Midnite Solar is a DC disconnect that provides overcurrent protection for any single inverter (250A panel mount breaker is included). The **MNDC175** comes with a DIN rail for five additional

DC breakers for DC loads, a charge controller disconnect, and a battery-status monitor. They also include a ground bus, and a 5/16" bonding battery-negative stud. Mounting holes for a 500 A shunt are built in.

Product Description

The MNDC175 175A DC Wiring Panel & Inverter Disconnect by Midnite Solar is a DC disconnect that provides overcurrent protection for any single inverter (250A panel mount breaker is included). The **MNDC175** comes with a DIN rail for five additional DC breakers for DC loads, a charge controller disconnect, and a battery-status monitor. They also include a ground bus, and a 5/16" bonding battery-negative stud. Mounting holes for a 500 A shunt are built in.

The white powder-coated aluminum chassis measures 17"H x 9"W x 4"D and weighs 7 lbs. Other main-breaker sizes are available. Left-side main-breaker placement is available by special order.

Product Attributes

- Dimensions: 1 × 1 × 1 cm
- Weight: 3.9 kg