

MNEDC175 : 175A, 125V DC Breaker by Midnite



Price: CAD \$179.00

SKU: MNEDC175

Product Categories: [Breakers](#), [Shop](#), [Wiring & BOS](#)

Product Tags: [125v dc](#), [150vdc](#), [175a](#), [battery breaker](#), [breaker](#), [canada](#), [dc](#), [dc breaker](#), [din rail](#), [inverter breaker](#), [inverter disconnect](#), [midnite](#), [midnite solar](#), [mnedc175](#), [mnedc175 canada](#), [solar](#)

Product Page: <https://www.modernoutpost.com/product/mnedc175-175a-125v-dc-load-center-breaker-by-midnite/>

Product Summary

The MNEDC175 is a 175A, 125V master breaker for batteries and inverters. Usually a part of a DC load centre. MidNite's breakers are rated to break the full rated load at the rated voltage repeatedly, with NO DAMAGE. Always use a properly sized breaker for disconnecting. All MidNite circuit breakers can be used at 100% rated current when mounted in a MidNite enclosure.

Product Description

The MNEDC175 is a 175A, 125V master breaker for batteries and inverters. Usually a part of a DC load centre. MidNite's breakers are rated to break the full rated load at the rated voltage repeatedly, with NO DAMAGE. Always use a properly sized breaker for disconnecting.

All MidNite circuit breakers can be used at 100% rated current when mounted in a MidNite enclosure.

Breaker Torque Value: 15 Ft-Lbs (20.4NM)

- NON POLARIZED - Environmental Rating - Type 1 (Indoor) - Width 1.5 inches (39mm) - 125VDC Panel Mount Breaker - 3/8" studs - AIC 50,000 at 125VDC - Breaker Torque Value: 15 Ft-Lbs (20.4NM) - Warranty - 5 yrs. - Listed for US & Canada

Product Attributes

- Dimensions: 1 × 1 × 1 cm
- Weight: .6 kg